

Model: ACD-330T Digital AC Clamp - On Multimeter



- TRMS sensing
- Dynamic Min/Max/Avg Recording
- In-rush Peak Current capture (1mS response)
- Dual Display of Frequency with Current or Voltage
- Continuity Buzzer and Diode Test
- Reading Hold function
- Maximum jaw opening 2.04" (52mm)
- Auto/Manual ranging
- Auto power off
- Low Battery indicator
- Overload protection on all ranges

UPC/DCI: 11930

Warranty: Limited Life Time Warranty

Size: 11.75x4.75x3.25 inch

Weight: 2.1 lb

Safety: designed to UL, ULc, CE, & IEC Standards

Instruction Manual: Yes

Hi-Resolution Image: Yes

SPECIFICATIONS

AC/DC Voltage: 0-399.9, 1000V $\pm(1\% \text{ Rdg} + 3 \text{ LSD})$

AC Current: 0-399.9, 1000A $\pm(1.5\% \text{ Rdg} + 3 \text{ LSD})$

Resistance: 0-399.9, 4000 Ω $\pm(3\% \text{ Rdg} + 5 \text{ LSD})$ @ 65-400Hz, 400-700A

Continuity Buzzer: $<10.0\Omega \pm(3.5\% \text{ Rdg} + 6 \text{ LSD})$

Frequency Measurements: 10.00-99.99Hz, 1000.0Hz $\pm(0.2\% \text{ Rdg} + 4 \text{ LSD})$

OPTIONAL ACCESSORIES

Part Number	Description
A47L	Power Line Splitter and Energizer
CT50-1	Amptan 5000A Clamp-on Current Transformer (50 to 1)
CT50-2	Amptan 3000A Clamp-On Current Transformer (50 to 1)
VRC-320	Set of Push-On Alligator Clips

REPLACEMENT PARTS (supplied with product)

Part Number	Description
MTL-90B	Set of Test Leads with Alligator Clips
CC-ACDC	Carrying Case