

Product Description:

Dranetz-BMI A-116 Current Probe, 10-600A RMS, Max condctr size 2.0"



Power Flow, Harmonic Measurement

For 3-Phase Measurements

Measurement Accuracy: 0.1%

Performance Characteristics of the A-116

Form Factor	Probe
Instrument application	Power Analyzer
Measurement Parameter	RF Power
Probe type	Passive
Minimum Frequency	50 Hz
Maximum Frequency	3 kHz
Measurement Accuracy	0.1 %
Minimum Input Current	10.0 Arms
Maximum Input Current	600.0 Arms

Programmability/Connectivity of the A-116

User Interface Proprietary

A-116 Compliance

CE Compliance	Not on file
UL Compliance	Not compliant

A-116 Power Requirements

Input Power Not required